

# PM-100DR | STEREO MINI RECEIVER



## Description

PM-100D is a stereo wireless in-ear monitor system. The PM-100D receiver is made of plastic and weighs only about 55 grams (without battery). It is one of the lightest transmitter pockets on the market. The receiver adopts bright OLED display. At the same time, it has built-in 1-99 frequency group channels for selection, and can select the cleanest channel in a complex environment. Digital transmission technology can convert the input sound into a digital signal and send it to the receiver. During the digital communication transmission process, it can protect the integrity of the audio and prevent the accumulation of noise, so it is very suitable for: live streaming and small bands.

## Product Specification

Receiving Method:	Antenna reception
Carrier Frequency Range:	521.25MHz-936.85MHz Integrated
Modulation Method:	mode
Comprehensive T.H.D:	<0.9%@1KHz
Stereo Separation:	≥65dB at 1KHz
Comprehensive Frequency Response:	20Hz-20KHz ±3dB
Batteries:	AA x 2
Current Consumption:	140mA (Typical)
Battery Life:	≤8 hours
Effective Working Distance:	80 meters (open place)
Output Socket:	Φ3.5mm stereo headphone socket
Output Power:	2×40mW at 1KHz (T.H.D: 0.03%) 198
Dimensions (mm):	(H) × 52.5 (W) × 25 (D)
Weight:	approximately 55g (without battery)