

RDA20 | DANTE AUDIO NETWORKED ENABLED SPEAKER SYSTEM



Description

The RDA20 is an integrated active full frequency speaker with network transmission and pure digital power amplifier. The speaker is powered by PoE/PoE+ network switch meaning no external power supply is required. The speaker includes a Class D amplifier which provides. Connect a network cable to communicate with the built-in Dante module to realize network audio signal transmission. By automatically assigning an IP address through the router DHCP, it can transmit signals with Dante's audio matrix in the LAN, and it is easy to set up a full digital network sound reinforcement system. Suitable for education, hospitals, small and medium-sized conference rooms, restaurants, houses of worship and other places.

Product Specification

Power Supply:	Standard PoE / PoE +
Supply Voltage:	37V-57V
Output Power:	PoE 10W / PoE + 20W
Frequency Response (-3dB):	85Hz-17KHz
Sound Pressure Level Output (-6dB):	110dB / aes continuous; 113dB / peak
Coverage Angle:	Horizontal / vertical 90° / 90°
Input jack:	Rj45
Size(mm):	132(W)×160(D) ×236(H)
Weight:	About 2.93kg
Accessories:	Wall bracket